




LP 128

USB to DMX interface



Compatible with the LED Player and Pro DMX software (in limited mode), and capable of several trigger options, this entry-level USB to DMX controller is ideal for DJs, modest budgets, small projects, testing and troubleshooting, or as a promotional package.



10th
YEAR
ANNIVERSARY

↓
FREE

DESIGNED & DEVELOPED
IN FRANCE

1st
YEAR
WARRANTY

CHROMATEQ



HARDWARE Options

DMX Output	128 Out channels PC and 128 Out Stand Alone
Zone	1 Zone, play 1 scene/sequence at time in Stand Alone
Memory	Internal memory (40 KB, 300 to 55 DMX step capacity)
Stand Alone Options	16-bit and fine channel management Cross Fade time between scenes Default start scene when power up
Triggers	4 Dry Contacts on 3~5V (On, On/Off, Release, Restart, Scene Priority, 15 contacts max) Infrared receiver (with optional IR remote) 10 scene selection, scene speed, general dimmer and next scene 1 NEXT button for scene selection
Power	5V DC (USB)
Dimension	H : 40mm(1.57in) / W : 50mm(1.97in) / D : 78mm (3.07in)
Housing	Extruded Aluminum
I/O Connectors	Mini USB 2.0, 3 pin XLR (XLR5 optional)
Operating Temperature	-40 to +85 C°
IP Rating	IP40
Certifications	CE, LVD, RoHS
International Warranty	1 years



SOFTWARE Options

LED Player	128 DMX Outputs
Pro DMX	100 DMX Outputs
Studio DMX	3D viewer in real time (Full mode)
Wi-Light 2 APP	Mobile software control (Android, iOS)
System Compatibility	Windows, iOS, Linux
Technical support	Worldwide, English, French, Chinese

FREE SOFTWARE
Download and Update



2010 - 2021 Chromateq SARL
Chromateq - All rights reserved

191 Allée de Lauzard
34980 St Gély du Fesc, FRANCE
Web: www.chromateq.com
Email: info@chromateq.com
Phone: +33 952210755
Wechat: Chromateq
WhatsApp: +8613422062209
QQ: 2908265661

Software & App download:

Software package download: <https://www.chromateq.com>
Wi Light 2 app download (iOS): <https://apps.apple.com/us/app/wi-light-2/id1523046687?l=fr>
Wi Light 2 app download (Android): <https://play.google.com/store/apps/details?id=com.chromateq.wilight2>

PC minimum configuration:
Windows / Mac OS / Linux (Device)
2Ghz CPU, 8 Gb RAM
2Gb RAM graphic card
500 Mb disk
1 USB port (Device)
1 Ethernet Port (for Art-Net & sACN)



www.chromateq.com
Contact • Support • Download