



### AT A GLANCE:

*RGB Color Mixing*



### Key Features:

- Tri-color LED Color Mixing
- Up to 12 hrs of Battery Life
- No Multi-Colored Shadows
- WDMX ready
- Perfect uplight for events

### About this light:

The WELL is a Wireless Event LED Luminaire designed specifically as a self contained uplight for any event. Powering each WELL light are 12, 3 W tri-color LEDs powered by self-contained 12 V battery which provides up to 12 hours of life. For control standard DMX ports are available or for a completely wireless solution, a WDMX wireless receiver is pre-installed. Simply plug a WDMX transmitter into your controller and you are good to go! Also available is a 6-slot road case that doubles as a gang charger for all the units simultaneously.

### DETAILED SPECIFICATIONS:

#### FEATURES

- Five distinct dimming curves
- 3-pin DMX input and output connectors
- Wireless DMX receiver built in
- LED display with password protection
- Split LED Array can be focused individually
- 12 hour battery life
- Movable foot on base of fixture for added positioning options
- Color Calibration

#### SPECIFICATIONS

- 16° optics  
Beam angle: 17°  
Field angle: 32°  
Lux: 225 @ 5 m
- Light source: 12 (3 W) tri-color LEDs, 50,000 hrs:  
red, green, blue (1,050 mA)
- Battery power: 12V 24Ah
- AC power for Charger: Auto-ranging 100 ~ 240 V 50/60 Hz
- Weight: 36.3 lbs / 16.5kg
- Size: 7.8 x 7.8 x 15.4 in / 198.5 x 198.5 x 392 mm

#### CONTROL FUNCTIONS

- 3, 4, 5, or 10-channel tri-color RGB LED wash light
- Operating modes  
3-channel: RGB control  
3-channel: HSV control  
4-channel: RGB, dimmer  
5-channel: RGB, dimmer, strobe  
10-channel: RGB, ID addressing, dimmer, strobe, macro, auto/custom, dimmer curve, auto speed
- RGB color mixing with or without DMX control
- Color temperature presets (3,200 ~ 10,000 K)
- Built-in automated programs via DMX
- Recall custom programs via DMX