

M1

Multimedia amplifier

M1 front



M1 rear



M1

Where other multizone amplifiers aren't all-in-one-devices, the M1 is a truly polyvalent solution. It has the flexibility of an advanced multizone mixer, combined with several digital options. By simply surfing to the webpage, one can get full control of the M1 basic functions. The M1 can be directly plugged into a basic LAN network.

No extra control software is needed, just a normal web-browser on your PC will do. Installation in commercial applications such as restaurants, clubs, bars, theaters, hotels, conference facilities, houses of worship and medical or professional offices.

As a simple example, when installed in a restaurant, the M-1 can provide popular music in the bar, cocktail music in the lounge, jazz in the waiting area, and classical music in the dining room.

Six microphones can be plugged in (XLR) with individual zone paging or mixing zone paging. Each room can have a digital wall mounted control panel for selecting a music source, and setting the volume.

FEATURES :

- Polyvalent
- Flexible + several digital options
- No extra software is needed

APPLICATIONS :

The M1 is perfect for use in commercial applications, such as clubs, hotels, theatres...



WP 18

Wall panel controller 8 zones

About Audac :

AUDAC provides a complete range of audio equipment such as amplifiers, loudspeakers, microphones, conference microphones and much more.

M1

Multimedia amplifier

PROFESSIONAL SOUND EQUIPMENT

PRODUCT FEATURES :	
Dimensions	482 x 132 x 350
Weight	8.2 kg
Unit height	3 HE
SYSTEM SPECIFICATIONS :	
Sensitivity microphone input line input	-60/-20 dB 600 Ohm balanced -20/+4 dB 10 K Ohm
Frequency response	20 Hz - 20 kHz
T.H.D. by 1 kHz	less than 0.1%
Signal to noise ratio	100 dB
Slew rate	+/- 30 V/sec
Digital control	
Serial port	RS 232
Remote zone control (1-4)	RS 485
Web based control Ethernet	
Zonal outputs 1 - 4	+3 dB 150 Ohm balanced
Output power per channel	100 Watt 8 ohm 150 Watt 4 Ohm
Bridged mode	300 Watt 8 Ohm
Power supply	240 V AC, 50-60 Hz
Max.power consumption	600 W

AUDAC
www.audac.be

 **CE** approved product

LIMITED WARRANTY

For a period of 2 years, starting from the original date of purchase, Audac products are covered against defects in workmanship or materials. The defective item will be repaired or replaced at the option of Audac, with no charge for materials or labour. You have to adequately pack up and dispatch the item prepaid to a Audac authorized distributor/service centre. Unauthorized repair shall void the warranty. Cosmetics and finish are not covered by this Audac warranty. The warranty is also voided if, in Audac's opinion, the items have failed due to user abuse, accidents, modifications or any type of misuse.

